


## Abmessungen / Dimensions / Dimensioni


### FDR A 8.0, 400V/3

| <b>Drehstrom 3x400V</b>   |                       |                    |                 |             |            |            |          |
|---|-----------------------|--------------------|-----------------|-------------|------------|------------|----------|
| <b>U prim: 3x400 V / 50Hz; U sek: 120, 160, 230, 280, 400 V</b> |                       |                    |                 |             |            |            |          |
| Es wird dringend empfohlen die Motoren über 230V zu betreiben!  |                       |                    |                 |             |            |            |          |
| Typ   | I <sub>max</sub><br>A | Ge-<br>wicht<br>kg | Best-Nr.        | Abmessungen |            |            | Bild     |
|   |                       |                    |                 | mm          |            |            |          |
|   |                       |                    |                 | a           | b          | c          |          |
| FDR-A 3.0/3   | 3,0                   | 12                 | 18061812        | 310         | 230        | 180        | 1        |
| FDR-A 5.0/3   | 5,0                   | 16                 | 18061822        | 310         | 230        | 180        | 1        |
| FDR-A 7.0/3   | 7,0                   | 18                 | 18062023        | 380         | 300        | 180        | 1        |
| <b>FDR-A 8.0/3</b>  | <b>10,0</b>           | <b>28</b>          | <b>18061832</b> | <b>400</b>  | <b>300</b> | <b>200</b> | <b>2</b> |
| FDR-A 11.3/3  | 15,0                  | 37                 | 18061852        | 400         | 400        | 200        | 2        |
| FDR-A 20/3  | 20,0                  | 45                 | 18061772        | 600         | 400        | 250        | 2        |

Schutzart IP 54  
Bild 1



Schutzart IP 54  
Bild 2



Masse / Dimensions / Dimensioni, mm